

Design list for variable airflow regulator RPM-V, RPMC-V - expanded

Version 2026-03-17

Sensor range

Design

Air flow	BELIMO compact solution (sensor, controller and actuator in one box)	Without the spring	Dynamic	Analog	LMV-D3-MF.1 MDK (5 N.m, NMV-D3-MF.1 MDK 10 N.m)	0...500 Pa	B00	
				Analog / MPBus	LMV-D3-MP (5 N.m, NMV-D3-MP 10 N.m, SMV-D3-MP 20 N.m)	0...500 Pa	B01	
				Modbus RTU / BACnet / MPBus	LMV-D3-MOD (5 N.m, NMV-D3-MOD 10 N.m, SMV-D3-MOD 20 N.m)	0...500 Pa	B02	
				KNX	LMV-D3-KNX (5 N.m, NMV-D3-KNX 10 N.m)	0...500 Pa	B04	
	BELIMO sensor and controller in one box and the actuator is separately	Without the spring	Dynamic	Analog / MP-Bus	Controller VRU-D3-BAC (VAV) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	0...500 Pa	B22	
				Modbus RTU / BACnet	Controller VRU-D3-BAC (VAV) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	0...500 Pa	B23	
				Analog / MP-Bus	Controller VRU-M1-BAC (VAV) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	0...600 Pa	B29	
				Modbus RTU / BACnet	Controller VRU-M1-BAC (VAV) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	0...600 Pa	B30	
		Speed actuator	Dynamic	Analog / MP-Bus	Controller VRU-D3-BAC (VAV) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	0...500 Pa	B22Q	
				Modbus RTU / BACnet	Controller VRU-D3-BAC (VAV) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	0...500 Pa	B23Q	
				Analog / MP-Bus	Controller VRU-M1-BAC (VAV) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	0...600 Pa	B29Q	
				Modbus RTU / BACnet	Controller VRU-M1-BAC (VAV) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	0...600 Pa	B30Q	
		Speed actuator / With the spring	Dynamic	Analog / MP-Bus	Controller VRU-D3-BAC (VAV) + NKQ24A-VST (10 N.m)	0...500 Pa	B22QF	
				Modbus RTU / BACnet	Controller VRU-D3-BAC (VAV) + NKQ24A-VST (10 N.m)	0...500 Pa	B23QF	
				Analog / MP-Bus	Controller VRU-M1-BAC (VAV) + NKQ24A-VST (10 N.m)	0...600 Pa	B29QF	
				Modbus RTU / BACnet	Controller VRU-M1-BAC (VAV) + NKQ24A-VST (10 N.m)	0...600 Pa	B30QF	
		With the spring	Dynamic	Analog / MP-Bus	Controller VRU-D3-BAC (VAV) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	0...500 Pa	B22F	
				Modbus RTU / BACnet	Controller VRU-D3-BAC (VAV) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	0...500 Pa	B23F	
				Analog / MP-Bus	Controller VRU-M1-BAC (VAV) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	0...600 Pa	B29F	
				Modbus RTU / BACnet	Controller VRU-M1-BAC (VAV) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	0...600 Pa	B30F	
	GRUNER compact solution (sensor, controller and actuator in one box)	Without the spring	Dynamic	Analog / PP-Bus	327VM-024-05 (5 N.m, 327VM-024-10 10 N.m, 327VM-024-15 15 N.m.)	0...500 Pa	G00	
				Modbus RTU	327VM-024-05-MB (5 N.m, 327VM-024-10-MB 10 N.m, 327VM-024-15-MB 15 N.m.)	0...500 Pa	G02	
				Analog / PP-Bus	327VM-024-05-DS4 (5 N.m, 327VM-024-10-DS4 10 N.m, 327VM-024-15-DS4 15 N.m.)	0...400 Pa	G06	
					327VM-024-05-DS6 (5 N.m, 327VM-024-10-DS6 10 N.m, 327VM-024-15-DS6 15 N.m.)	0...600 Pa	G07	
		With the spring	Static	Modbus RTU	327VM-024-05-DS4-MB (5 N.m, 327VM-024-10-DS4-MB 10 N.m, 327VM-024-15-DS4-MB 15 N.m.)	0...400 Pa	G12	
327VM-024-05-DS6-MB (5 N.m, 327VM-024-10-DS6-MB 10 N.m, 327VM-024-15-DS6-MB 15 N.m.)					0...600 Pa	G13		
Dynamic				Analog / PP-Bus	Controller GUAC-DM3 + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...300 Pa	G21	
					Controller GUAC-DM3-MB + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...300 Pa	G23	
	Modbus RTU	Controller GUAC-DM3 + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...300 Pa	G28				
		Controller GUAC-DM3-MB + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...300 Pa	G30				
SIEMENS compact solution (sensor, controller and actuator in one box)	Without the spring	Dynamic	Analog / PP-Bus	GDB181.1E/3 (5 N.m, (GLB181.1E/3 10 N.m)	0...500 Pa	S00		
			Modbus RTU	GDB181.1E/MO (5 N.m, (GLB181.1E/MO 10 N.m)	0...500 Pa	S02		
			KNX	GDB181.1E/KN (5 N.m, (GLB181.1E/KN 10 N.m)	0...500 Pa	S04		
			BACnet	GDB181.1E/BA (5 N.m, (GLB181.1E/BA 10 N.m)	0...500 Pa	S05		
	sensor and controller in one box and the actuator is separately	Without the spring	Dynamic	Without communication	Controller ASV181.1E/3 + GDB141.1E (5 N.m, GEB141.1E 20 N.m, GBB141.1E 25 N.m, GIB141.1E 35 N.m)	0...500 Pa	S22	
		Speed actuator / With the spring			Controller ASV181.1E/3 + GPC131.1A (60s/15s) 4 N.m	0...500 Pa	S22QF	
		With the spring			Controller ASV181.1E/3 + GPC131.1A (4 N.m, GMA131.1E 7 N.m, GCA131.1E 18 N.m)	0...500 Pa	S22F	
Pressure	BELIMO sensor and controller in one box and the actuator is separately	Without the spring	Dynamic	Analog / MP-Bus	Controller VRU-D3-BAC (STP) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	0...500 Pa	B63	
				Modbus RTU / BACnet	Controller VRU-D3-BAC (STP) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	0...500 Pa	B64	
				Analog / MP-Bus	Controller VRU-M1-BAC (STP) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	0...600 Pa	B75	
					Controller VRU-M1-BAC (STP) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	0...600 Pa	B78	
		Speed actuator	Dynamic	Analog / MP-Bus	Controller VRU-D3-BAC (STP) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	0...500 Pa	B63Q	
				Modbus RTU / BACnet	Controller VRU-D3-BAC (STP) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	0...500 Pa	B64Q	
				Analog / MP-Bus	Controller VRU-M1-BAC (STP) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	0...600 Pa	B75Q	
					Controller VRU-M1-BAC (STP) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	0...600 Pa	B78Q	
		Speed actuator / With the spring	Dynamic	Analog / MP-Bus	Controller VRU-D3-BAC (STP) + NKQ24A-VST (10 N.m)	0...500 Pa	B63QF	
				Modbus RTU / BACnet	Controller VRU-D3-BAC (STP) + NKQ24A-VST (10 N.m)	0...500 Pa	B64QF	
				Analog / MP-Bus	Controller VRU-M1-BAC (STP) + NKQ24A-VST (10 N.m)	0...600 Pa	B75QF	
					Controller VRU-M1-BAC (STP) + NKQ24A-VST (10 N.m)	0...600 Pa	B78QF	
		With the spring	Dynamic	Analog / MP-Bus	Controller VRU-D3-BAC (STP) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	0...500 Pa	B63F	
				Modbus RTU / BACnet	Controller VRU-D3-BAC (STP) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	0...500 Pa	B64F	
				Analog / MP-Bus	Controller VRU-M1-BAC (STP) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	0...600 Pa	B75F	
					Controller VRU-M1-BAC (STP) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	0...600 Pa	B78F	
	GRUNER compact solution (sensor, controller and actuator in one box)	Without the spring	Dynamic	Analog / PP-Bus	327VM-024-05 (CCPC) (5 N.m, 327VM-024-10 (CCPC) 10 N.m, 327VM-024-15 (CCPC) 15 N.m.)	0...500 Pa	G50	
				Modbus RTU	327VM-024-05-MB (CCPC) (5 N.m, 327VM-024-10-MB (CCPC) 10 N.m, 327VM-024-15-MB (CCPC) 15 N.m.)	0...500 Pa	G52	
				Analog / PP-Bus	327VM-024-05-DS4 (CCPC) (5 N.m, 327VM-024-10-DS4 (CCPC) 10 N.m, 327VM-024-15-DS4 (CCPC) 15 N.m.)	0...400 Pa	G53	
					327VM-024-05-DS6 (CCPC) (5 N.m, 327VM-024-10-DS6 (CCPC) 10 N.m, 327VM-024-15-DS6 (CCPC) 15 N.m.)	0...600 Pa	G54	
		With the spring	Static	Modbus RTU	327VM-024-05-DS4-MB (CCPC) (5 N.m, 327VM-024-10-DS4-MB (CCPC) 10 N.m, 327VM-024-15-DS4-MB (CCPC) 15 N.m.)	0...400 Pa	G59	
					327VM-024-05-DS6-MB (CCPC) (5 N.m, 327VM-024-10-DS6-MB (CCPC) 10 N.m, 327VM-024-15-DS6-MB (CCPC) 15 N.m.)	0...600 Pa	G60	
				Dynamic	Analog / PP-Bus	Controller GUAC-PM-DD3 + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...300 Pa	G62
						Controller GUAC-PM-DD3-MB + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...300 Pa	G64
	Static	Analog / PP-Bus	Controller GUAC-PM1 + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)		0...100 Pa	G70		
Controller GUAC-PM3 + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)			0...300 Pa		G71			
Modbus RTU		Controller GUAC-PM6 + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...600 Pa	G72				
		Controller GUAC-PM1-MB + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...100 Pa	G76				
GRUNER sensor and controller in one box and the actuator is separately	Without the spring	Dynamic	Analog / PP-Bus	Controller GUAC-PM3-MB + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...300 Pa	G77		
				Controller GUAC-PM6-MB + 227C-024-05-V/ST06 (5 N.m, 227C-024-10-V/ST06 10 N.m, 227C-024-15-V/ST06 15 N.m, 363C-024-20-V/ST06 20N.m)	0...600 Pa	G78		
			Modbus RTU	Controller GUAC-PM-DD3 + 341C-024-05-V/ST06 (5 N.m, 361C-024-10-V/ST06 10 N.m, 361C-024-20-V/ST06 20 N.m)	0...300 Pa	G62F		
				Controller GUAC-PM-DD3-MB + 341C-024-05-V/ST06 (5 N.m, 361C-024-10-V/ST06 10 N.m, 361C-024-20-V/ST06 20 N.m)	0...300 Pa	G64F		
	With the spring	Static	Analog / PP-Bus	Controller GUAC-PM1 + 341C-024-05-V/ST06 (5 N.m, 361C-024-10-V/ST06 10 N.m, 361C-024-20-V/ST06 20 N.m)	0...100 Pa	G70F		
				Controller GUAC-PM3 + 341C-024-05-V/ST06 (5 N.m, 361C-024-10-V/ST06 10 N.m, 361C-024-20-V/ST06 20 N.m)	0...300 Pa	G71F		
			Modbus RTU	Controller GUAC-PM6 + 341C-024-05-V/ST06 (5 N.m, 361C-024-10-V/ST06 10 N.m, 361C-024-20-V/ST06 20 N.m)	0...600 Pa	G72F		
				Controller GUAC-PM1-MB + 341C-024-05-V/ST06 (5 N.m, 361C-024-10-V/ST06 10 N.m, 361C-024-20-V/ST06 20 N.m)	0...100 Pa	G76F		
With the spring	Static	Modbus RTU	Controller GUAC-PM3-MB + 341C-024-05-V/ST06 (5 N.m, 361C-024-10-V/ST06 10 N.m, 361C-024-20-V/ST06 20 N.m)	0...300 Pa	G77F			
			Controller GUAC-PM6-MB + 341C-024-05-V/ST06 (5 N.m, 361C-024-10-V/ST06 10 N.m, 361C-024-20-V/ST06 20 N.m)	0...600 Pa	G78F			
		Analog / MP-Bus	Controller VRU-M1R-BAC (RP) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	-75...+75 Pa	B91			
			Controller VRU-M1R-BAC (RP) + LM24A-VST (5 N.m., NM24A-VST 10 N.m, SM24A-VST 20 N.m)	-75...+75 Pa	B92			
Pressure in the room	Without the spring	Static	Analog / MP-Bus	Controller VRU-M1R-BAC (RP) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	-75...+75 Pa	B91Q		
				Controller VRU-M1R-BAC (RP) + LMQ24A-VST (4 N.m., NMQ24A-VST 8 N.m)	-75...+75 Pa	B92Q		
			Modbus RTU / BACnet	Controller VRU-M1R-BAC (RP) + NKQ24A-VST (10 N.m)	-75...+75 Pa	B91QF		
				Controller VRU-M1R-BAC (RP) + NKQ24A-VST (10 N.m)	-75...+75 Pa	B92QF		
	Speed actuator / With the spring	Static	Analog / MP-Bus	Controller VRU-M1R-BAC (RP) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	-75...+75 Pa	B91F		
				Controller VRU-M1R-BAC (RP) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	-75...+75 Pa	B92F		
			Modbus RTU / BACnet	Controller VRU-M1R-BAC (RP) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	-75...+75 Pa	B91QF		
				Controller VRU-M1R-BAC (RP) + LF24-VST (4 N.m, NF24A-VST 10 N.m, SF24A-VST 20 N.m)	-75...+75 Pa	B92QF		